E797-MOD1 60AMP VOLTAGE CONVERTER 24V – 12V




24V – 12V VOLTAGE CONVERTER 60AMP
HIGH SPECIFICATION
MANUFACTURED IN THE UK

- **PART NO: E797 – MOD1**
- **TYPE: SWITCH MODE DROPPER**
- **RATING: 60 AMP**
- **MAX CONTINUOUS O/P CURRENT: 60 AMP**
- **PEAK OUTPUT CURRENT: 80 AMP**
- **INPUT VOLTAGE: 18 – 30V DC**
- **OUTPUT VOLTAGE: 13.5V DC**
- **OVERLOAD PROTECTION: YES**
- **OUTPUT PROTECTED: YES**
- **POLARITY PROTECTED: YES**
- **OPERATING TEMPERATURE: - 40 DEG.C TO + 70 DEG.C**
- **HIGH TEMP PROTECTED: YES**
- **SHORT CIRCUIT PROTECTION: YES**
- **OVER VOLTAGE PROTECTION: YES**
- **EFFICIENCY: > 90%**
- **LOAD REGULATION: 0.3V**
- **DIMENSIONS: 330mm X 230mm x 80mm**
- **Mountings: 4 x Ø 6mm Holes**
- **Weight: 3058g**
- **CONSTRUCTION: 4 X E710 15A DROPPER MOUNTED ON A SINGLE ALUMINIUM PLATE**

MODELS ALSO AVAILABLE: 15AMP / 30AMP / 45AMP / 75AMP / 90AMP

OEM AND TRADE ENQUIRIES WELCOME



EURO MANUFACTURING AND MARKETING LIMITED
Euro Works, 11-13 High Street, Wem, Shropshire SY4 5AA, England.
Tel: +44 (0) 1939 235073 Fax: +44 (0) 1939 235074
Email: sales@eurogroup-gb.com OR sales@battery-management-voltage-converter.com
Web Site: www.eurogroup-gb.com OR www.battery-management-voltage-converter.com

BEFORE INSTALLATION YOU NEED TO PURCHASE:

RECOMMENDED MINIMUM CABLES SIZES:
INPUT (RED): 25mm² CONDUCTOR CROSS SECTION (196/0.4mm)
OUTPUT (BLUE): 25mm² CONDUCTOR CROSS SECTION (196/0.4mm)
GROUND (BLACK)): 25mm² CONDUCTOR CROSS SECTION (196/0.4mm)
CONTROL (BROWN): 1.0mm² CONDUCTOR CROSS SECTION (32/0.2mm)

INSTALLATION INSTRUCTIONS:

1. **CONNECT THE BLUE OUTPUT LEAD CONNECTION TO THE +VE CONNECTION ON YOUR 12V EQUIPMENT**
2. **CONNECT ONE BLACK LEAD CONNECTION TO THE –VE CONNECTION OF THE 12V EQUIPMENT**
3. **CONNECT ONE BLACK LEAD CONNECTION TO GROUND, IE: THE VEHICLE CHASSIS OR TO THE –VE CONNECTION OF THE 24V SUPPLY / BATTERY**
4. **CONNECT THE RED INPUT LEAD CONNECTION TO YOUR 24V +VE SUPPLY / BATTERY**
5. **THE BROWN CONTROL LEAD CONNECTION GIVES YOU THE OPTION TO SWITCH THE VOLTAGE CONVERTER ON AND OFF USING A STANDARD LOW CURRENT SWITCH.**
6. **ALTERNATIVELY YOU CAN CONNECT THE BROWN CONTROL CONNECTION LEAD DIRECTLY TO THE POSITIVE INPUT, IE: THE +VE CONNECTION ON THE 24V BATTERY, WHICH WILL ENABLE YOU TO RUN THE VOLTAGE CONVERTER ALL THE TIME.**

IF IN DOUBT, PLEASE CONSULT AN AUTOMOTIVE ELECTRICIAN OR TELEPHONE US ON 01939 235073

WHY NOT VISIT OUR WEBSITES TO VIEW THE OTHER PRODUCTS WE MANUFACTURE:

http://www.battery-management-voltage-converter.com
This site covers our:

- **Battery Management Systems**
- **Split Charge Controllers**
- **DC-DC Battery Chargers**
- **DC-DC Voltage Converters**
- **Trailer Voltage Converters**
- **Battery Status Indicators**
- **Voltage Sensitive Switches.**

http://www.eurogroup-gb.com
This site covers our Range of:

- **Water Level Monitors**
- **Water Level Probes**
- **Temperature Monitors**
- **Temperature Probes**
- **Air Conditioning Fan Control Units**
- **Vehicle Flashers and Interrupters**
- **Light Control Units**
- **Oil Level Monitors**
- **Oil Level Probes**
- **Hydraulic Control Units**
- **Audible Warning Devices**
- **Reversing Alarms**
- **Timers**
- **Vehicle Safety and Security Units**
- **Digital Speed Switches**
- **Solenoid Controllers**
- **Relays, Connectors, Lamps, Switches**
- **Earth Straps**
- **Looms and Wiring Harnesses**
- **Transformer and Coil Winding**
- **Mechanical Assembly**
- **Special Purpose Electrical / Electronic Assembly**
- **Encapsulation and Formal Coating**
- **Vacuum Formed Parts**
- **Printed Circuit Board Assembly**